





## BMMTRMS1 Digital Multimeter Set

### PRODUCT DETAILS

- Precise and reliable, the Bahco BMMTRMS1 digital multimeter is the perfect solution for users looking for a tester that is easy and safe to use for measuring AC/DC voltage, current, frequency, resistance, capacitance, continuity, polarity and temperature.
- It includes:
  - Multimeter bag with multimeter strap holder
  - Needle probe set with silicone leads 1m long: Cat III 1000V, 10A
  - Alligator clip test probe lead sets, spring-loaded copper clips with wide 12.7 mm (0.5 inch) jaw opening and serrated teeth, 1m long: Cat III 1000V, 10A
  - T° sensor probe lead 1 m long
  - Multimeter PC connectivity USB cable 1.2 m long
  - USB memory stick loaded with PC Link connectivity software and user manual in the following 12 languages: English-French-Spanish-Swedish-Turkish-Russian-Portugese-Italian-Greek-Slovenian-Czech-Polish
  - Calibration report
  - 1 battery 6F22 (9V) included
- Specifications:
  - True RMS measurement
  - Non contact voltage feature
  - Relative measurement
  - Auto power-off
  - Data hold
  - Backlight function
- Auto/manual range
- Polarity indication
- Diode test
- Continuity test
- Low battery power indication
- DC voltage range: 600mV  $\pm 0.5\%$ , 6V/60V/600V  $\pm 0.8\%$ , 1000V  $\pm 1.0\%$
- AC voltage range: 600mV/6V/600V  $\pm 1.0\%$ , 1000V  $\pm 1.5\%$
- DC current: 600uA/6mA/60mA/600mA/10A  $\pm 1.5\%$
- CAT rating: CATIII 1,000V CATIV 600V
- Resistance: 600 $\Omega$ /6K $\Omega$ /60K $\Omega$ /600K $\Omega$ /6M $\Omega$   $\pm 0.5\%$ , 60M $\Omega$   $\pm 1.5\%$
- Capacitance: 6nF  $\pm 3.0\%$ , 600nF/6uF/60uF/300uF  $\pm 5.0\%$
- Logic frequency: 10Hz~1MHz  $\pm (0.1\%+3)$
- Linear frequency: 10Hz~10KHz  $\pm (0.05\%+8)$
- Duty cycle: 1%~99%
- Temperature: -55°C~1000°C  $\pm (2\%+2)$
- Fuse protection: 0.63A/1000Vx1 for  $\mu$ A and mA ranges and 10A/1000Vx1 for 10A range

### PRODUCT ATTRIBUTES

Product		
<b>BMMTRMS1</b>	155 x 60 x 225 mm	0.8 kg

Follow the Fish!

